

From CLUTTER to CLARITY

Revamp your SHACK DC power
With

SHAKPR-30



Manage **DC POWER** of your LAB/Radio shack with single source multiple device powering

SHAKPR30 is a DC POWER Monitoring and Distribution unit. With one input from your existing DC POWER SOURCE – it facilitates multiple device connectivity through the 9 Binding-post.

The left 6 are meant for high current and the rest 3 nos. at the extreme right can be switched ON/OFF through the toggle switch individually which you can use it for manual sequential power. These 3 binding post are meant for low current up to 5Amps whereas, the 3+3 nos. is meant for 30A current.

Each binding post can be used multiple ways - plugged through external male plugs, a wire can be twisted or a wire can be inserted in the hole of the binding post. The holes in the binding post are visible once you unscrew the red/black top.

This gives your flexibility to mount various devices through SHKPR30.

SHKPR30 also displays Voltage, Current and Power through its display so you are always monitoring your DC power instantly.

Specification:

- INPUT VOLTAGE – 10-13.8VDC
- MAX. OVERALL CURRENT – 30AMPS
- DIMENSION – 35cm x 8cm x 8cm (INCLUDING CONNECTOR TOP)
- POWER ON SWITCH – SOFT TOUCH PUSH BUTTON
- INPUT BINDING POST – ONE
- OUTPUT HIGH CURRENT BINDING POST – SIX
- OUTPUT LOW CURRENT BINDING POST - THREE
- INDIVIDUAL SWITCH FOR LOW CURRENT BINDING POST – THREE
- OUTPUT CURRENT FOR LOW CURRENT BINDING POST – 5AMPS MAX.
- OUTPUT CURRENT FOR HIGH CURRENT BINDING POST - 30AMPS. MAX
- MINIMUM DISPLAY CURRENT – 1A
- DC INPUT – REVERSE POLARITY PROTECTED
- OVERLOAD LED- TURNS ON DURING MORE THAN 30A LOAD
- PACKAGING DIMENSION APPROX.- 14 x 16 x 10cm

SHIPS with a PACK OF 10 MALE PLUGS

SHAKPR-30

CEDA-Labz www.CEDA-Labz.com

Contact us at: +91 9810338939 cedalabz@gmail.com

CEDA-Labz