

LUNARIS-G6+

VHF UHF 900MHz 1.2GHz & 2.4GHz

SWR & POWER METER 2M - 12.5CM

DUAL SENSOR **PENTABAND** RF POWER METER



Highly accurate & fast for measuring Forward, Reflected Peak & Average Power & VSWR
CALIBRATED with ROHDE & SCHWARZ SMY 01 Signal Generator

MODEL NO.

LUNARIS-G6 +

SPECIFICATIONS

FREQUENCY RANGE

140-525 MHz / 900MHz / 1.2GHz / 2.4GHz

CALIBRATION POINT

145MHz / 435 MHz / 930MHz/1.2GHz/2.4GHz

POWER RANGE (AUTO-RANGING)

0 -200W (100 mw min. display)

ACCURACY

(+ / - 6%)

MINIMUM POWER FOR SWR

1 WATT

MAX. POWER

**200 WATT VHF/UHF
50WATT 900MHz/1.25GHz /2.4GHz**

REFLECTED POWER ALARM +
BRIGHT LED

**USERS PROGRAMMABLE - 1 WATT ONWARDS TILL the desired level.
Alarm and Visual indicator**

AUTO SHUT OFF

IF there is no signal the display shuts off – the time is user defined

FRONT PANEL
OLED TEXT DISPLAY

BRIGHT AMBER OLED DISPLAY FOR EASY READING
DISPLAYS FWD/REF & VSWR
DISPLAY AUTO SHUT OFF

BAND SWITCH

SELECT HF & VHF/UHF /900MHz/1.2GHz/2.4GHz

POWER SWITCH
3 SOFT TOUCH PUSH BUTTON
SWITCH –USER
PROGRAMMABLE

SOFT TOUCH PUSH BUTTON
SETS REFLECTED POWER WITH ALARM IN BARGRAPH OR ACTUAL VALUE

POWER DISPLAY SEQUENCE

DISPLAYS PEAK POWER FOR 2 SECONDS INITIALLY AND THEN SHOWS AVERAGE POWER

REAR PANEL

TX /ANT Connector
TX/ANT Connector
Power Source

2x SO239 50 ohms Coax. Connector for VHF/UHF /900mhz
2x SMA Female 50 ohms Coax. Connector for 1.2GHz/2.4GHz
13.8V DC @150ma

PENTABAND
VHf -2.4Ghz
Ultimate range



CEDA-Labz www.CEDA-Labz.com or contact us at: +91 9810338939

cedalabz@gmail.com

CEDA-Labz